

Tender text

TXS-81SX

Multifrequency headband microphone transmitter,

with UHF PLL technology.

- 16 selectable UHF channels (863-865 MHz), can be synchronised with receivers TXS-81 or TXS-81PLUG via ACT function
- Compact design
- Continuously adjustable volume
- LCD for indicating group/channel, frequency and battery status
- Electret headband microphone (cardioid polar pattern) with latchable 3.5 mm plug
- Belt clip
- Power supply via 1 x 1.5 V battery AA size (not supplied)

Licence-free in the EU.

Specifications:

General information

Description	pocket transmitter
Carrier frequency range	863-865 MHz
Audio frequency range	40-15,000 Hz
Channels	1
Operating time	> 5 h
Admiss. ambient temp.	0-40 °C
Specifications transmitter	
Transmitting power	10 mW
Power supply transmitter	1 x 1.5 V batt. AA size
Width transmitter	68 mm
Height transmitter	140 mm
Depth transmitter	27 mm
Weight transmitter	88 g
Connections transmitter	1 x 3.5 mm jack

Brand: IMG STAGELINE

Type: TXS-81SX

Quantity: 1

Packing dimensions (W x H x L): 0.2 x 0.06 x 0.22 m

Gross weight: 0.254 kg

Net weight: 0.088 kg

Item weight (w/o accessories): 0.088 kg